

NVR Firmware												
xxxxx.1.103507.108.nbn												
GCI-	K1603B	K1607B	K1503B	K1523D	K1523V	K1585V(-1)	K1526V(H)	K1586V(H)	K1526T(H)	K10589T(-1)	K1812W	H0812W
Camera Firmware version	gr20140124NSA										gr20131004NSA	
Streaming/ Recording	12fps	12fps	√	√	12fps	√	√	√	√	√	√	12fps
Resolution	√	√	√	√	√	√	√	√	√	√	√	√
FPS	√	√	√	√	√	√	√	√	√	√	√	√
Bitrate	√	√	√	√	√	√	√	√	√	√	manual	manual
Image Settings	√	√	√	√	√	√	√	√	√	√	√	√
Exposure Settings	√	√	√	√	√	√	√	√	√	√	√	√
Motion Area Setup	x1	x1	x1	x1	x1	x1	x1	x1	x1	x1	x1	x1
Alarm	manual	manual	manual	manual	manual	manual	manual	manual	manual	manual	manual	manual
PTZ	-	-	-	-	-	-	-	-	-	-	-	-
GCI-	F0505B	G0509B	K1555Z	K0779P	K1779P	K2505B	H2505B	K1523V(S)	K1526V(S)	D2201AR	C0735P	C0745P
Camera Firmware version	gr20140124NSA					gr20131205NSX				20130530		
Streaming/ Recording	√	√	√	√	√	√	√	√	√	√	√	√
Resolution	max. 1920x1080		√	√	√	√	√	√	√	√	√	√
FPS	√	√	√	√	√	√	√	√	√	√	√	√
Bitrate	√	√	√	√	√	manual	manual	manual	manual	manual	manual	manual
Image Settings	√	√	√	√	√	√	√	√	√	-	√	√
Exposure Settings	√	√	√	√	√	manual	manual	manual	manual	-	√	√
Motion Area Setup	x1	x1	x1	x1	x1	DC	DC	DC	DC	x1	x1	x1
Alarm	manual	manual	manual	manual	manual	manual	manual	manual	manual	manual	manual	manual
PTZ	-	-	√	√	√	-	-	-	-	x2	√	√

x1= Detection Level, Pixel Interval and Time not adjustable

x2= PTZ needs to be activated in Encoder OSD

DC = Direct Configure: Motion Area Setup needs to be adjusted in camera OSD

12fps = These models support only 12fps in FullHD. The NVR recording needs to be adjusted accordingly.

Alarm functionality needs to be setup in Camera OSD by adding HTTP command "alarm_xx" in the HTTP notification field in the webinterface of camera; xx values: 00=camera1; 01=camera2; 02=camera3; ... ; 15=camera16